



AVC8000S

8xD1 Video Frame Grabber

Document version: A.00

HARDWARE REFERENCE MANUAL



**Advanced Micro
Peripherals**

THE EMBEDDED VIDEO EXPERTS

Definitions

AMP and Advanced Micro Peripherals are the trading names for Advanced Micro Peripherals Inc. and Advanced Micro Peripherals Ltd.

Disclaimer

This document contains information on a new product. Specifications and information herein are subject to change without notice. AMP reserves the right to make changes to any products herein to improve functioning and design. Although the information in this document has been carefully reviewed and is believed to be reliable, AMP does not assume any liability arising out of the application or use of any product or circuit described herein. Nothing in this document is to be taken as a license to operate under or a recommendation to infringe any patents.

AMP does not recommend the use of any of its products in life support applications wherein a failure or malfunction of the product may directly threaten life or injury. The user of AMP products in life support applications assumes all risk of such use and indemnifies AMP against all damages. All information contained in this document is proprietary to AMP and may not be reproduced or disclosed to any third parties without the written consent of AMP. The circuit design, EPLD programs and artworks are copyright AMP 2008.

The information contained in this document has been carefully checked and is believed to be reliable. However, Advanced Micro Peripherals Ltd (AMP) makes no guarantee or warranty concerning the accuracy of said information and shall not be responsible for any loss or damage of whatever nature resulting from the use of, or reliance upon, it. AMP does not guarantee that the use of any information herein will not infringe upon the patent, trademark, copyright, or other rights of third parties, and no patent or other license is implied hereby

AMP reserves the right to make changes in the products or specifications, or both, presented in this document at any time and without notice.

Warranty

This product is supplied with a 1 year limited warranty. The product warranty covers failure of any AMP manufactured product caused by manufacturing defects. AMP will make all reasonable effort to repair the product or replace it with an identical variant. AMP reserves the right to replace the returned product with an alternative variant or an equivalent fit, form and functional product.

Trademarks

Tiny486, Tiny486, Tiny586DX, Tiny786LP, Mobile786EBX, Tiny886, TinyLX, VAC104, VAC104plus, The Embedded Video Experts are trademarks of Advanced Micro Peripherals. All other trademarks recognized.

Revision History

Document version	Date	Comments	Approved
A.00	26 th July 2013	Initial release – based on Rev A.00 PCB	BK



Advanced Micro Peripherals operates a company-wide quality management system, which has been certified by QMS International plc as compliant with ISO9001:2000

Contents

1:	Introduction	4
	Features.....	5
	Technical specification	7
	Functional summary.....	8
	Ordering information	9
2:	Installation	10
	System requirements	10
	Jumpers and Connectors.....	11
A:	Contacting AMP.....	14

Introduction

The AVC8000S is a high-performance 8-channel video capture and overlay controller on a single PCIe form factor card. The AVC8000S provides a powerful and flexible solution for capturing up to eight concurrent analog video inputs for local system display or software analysis and processing, ideal for embedded Situational Awareness systems in the most demanding environment.

The AVC8000S allows each of the 8 video channels to be captured at full D1 size, all at full frame rate. The video can be scaled, cropped and positioned under software control.


The captured video data can be streamed continuously to system memory or disk for either immediate local display or further processing. The capture engine of the AVC8000S features hardware color space conversion to present the captured video data in the format best suited to the end application.

AMP can provide custom configurations (subject to a minimum order quantity) for the AVC8000S. Please contact our Sales team (see [A: Contacting Advanced Micro Peripherals](#)) to discuss your requirements.

Features

- Real time video capture to system memory or overlay to system VGA screen
- 8 Live NTSC/PAL video inputs
- 8 x D1 size capture at full frame rate
- Arbitrary video windows sizing, cropping and scaling
- Efficient PCI DMA Cycle operation
- Robust PCIe construction
- Low power operation
- Windows DirectShow/DirectDraw operation
- Linux Video4Linux2 support
- Single +3.3V operation

AVC8000S 'at a glance'



Technical specification

Video Input:	8 channels composite video Monochrome/color NTSC or PAL 8 10-bit Analog-to-Digital Converters Anti-aliasing filters on inputs 1V peak-to-peak (75 Ohm input impedance) Contrast adjustable from 0 – 255% of original Saturation adjustable from 0 – 200% of original Hue adjustable from -36deg to +36deg Brightness can be adjusted from -128 to 127 steps Software adjustable sharpness, gamma and noise suppression
Video Overlay:	Video Overlay to host system VGA buffer Flexible arrangement of overlay windows Video capture to system memory buffer Supported Capture Formats: RGB555 / RGB565 / YCbCr 4:2:2 / YCbCr 4:1:1
Software:	SDK for Windows and Linux Window DirectShow/DirectDraw support Linux Video4Linux2 support
PC/104-Express:	Single x1 PCI Express Link
Power:	Single +3.3V supply
Environmental:	0 to 60°C -40 to +85°C (option)
Physical Size:	Standard PCIe card form

Functional summary

Signal Sources

The AVC8000S is designed to simultaneously capture and display up to 8 separate and unrelated video sources. Each video frame grabber channel includes a digital NTSC/PAL video decoder.

Video Digitization

Composite NTSC or PAL video is input to the AVC8000S through the MMCX connectors VIN_A1 to VIN_A8. The video is AC-coupled and fed to the on-board decoders of the individual frame grabbers. The video decoders automatically detect whether the incoming video signal is NTSC or PAL and generates the correct timing output signals. Each video channel is first decoded to chrominance and luminance signals and then digitized by high speed analog-to-digital (A2D) converters.

Real time Live Video Overlay

Digital video data streams from are routed across the PC/104-Express bus to the display buffer of the host CPU for overlaying on the VGA Scree. The Overlay Windows can be scaled, cropped and positioned anywhere on the VGA screen.

The digitized video streams from the AVC8000S may also be directed to a memory buffer within the host CPU for frame grabber applications where the information may need further processing (such as software encoding and recording).

Host Interface

The AVC8000S uses a single x1 PCI Express link.

Ordering information

The following part number(s) can be used when ordering:

AVC8000S 8-Channel Video Frame Grabber (0°C to +60°C)

AVC8000S-EXT Extended temperature version (-40°C to +85°C).

Cable-AVC8000S 8x MMCX to BNC cables (video inputs)

Anti-static handling

The board(s) supplied contain electrostatic components that are susceptible to permanent damage from electrostatic discharge (static electricity). To prevent electrostatic discharge, the boards are supplied in anti-static packaging.

When handling a board, observe the following anti-static precautions to alleviate risk of damage:

- Remove the board(s) from the packaging only when you are working on an anti-static, earthed surface and wearing an anti-static wrist strap.
- Retain the anti-static packaging that the board(s) were supplied in. If you remove a board from a system, store it in this packaging.

2:


Installation

System requirements

PCIe Host computer

x86 CPU
512 Mbytes memory or more
PCI-Express bus
Windows-XP-E or Linux

Jumpers and Connectors



VIN PAL/NTSC Video Input

Low profile MMCX Connectors for connecting video sources to the AVC8000S.

MMCX	Signal
VIN_A1	Channel 1 video input
VIN_A2	Channel 2 video input
VIN_A3	Channel 3 video input
VIN_A4	Channel 4 video input
VIN_A5	Channel 5 video input
VIN_A6	Channel 6 video input
VIN_A7	Channel 7 video input
VIN_A8	Channel 8 video input

K1

PCI- Express bus.

JP1

Reserved for factory use.

3:

AVC8000S Card Installation

This section describes AVC8000S hardware and software installation procedures. Software for the AVC8000S is provided on a CD.

The optional video input cables (from Cable-AVC8000S) should be plugged into VINx to provide live video input to the AVC8000S.

For most recent BIOS and operating system software, the AVC8000S is automatically detected.

Software driver installation should be done from the supplied CD. Further instructions (and demo programs) for specific operating systems are provided on the driver CD.

A:

Contacting AMP

Sales

AMP's sales team is always available to assist you in choosing the board that best meets your requirements. Contact your local sales office or hotline.

Sales office US

Advanced Micro Peripherals Inc.
Suite 1117, 149 Madison Ave
New York
NY, 10016
USA

Tel: +1 212 951 7205
Fax: +1 212 951 7206
E-mail: sales@amp-usa.com
Web: www.amp-usa.com

Sales office UK

Advanced Micro Peripherals Ltd.
1 Harrier House, Sedgeway Business Park
Witchford, Cambridge,
CB6 2HY
United Kingdom

Tel: +44 (0)1353 659500
Fax: +44 (0)1353 659600
E-mail: sales@ampltd.com
Web: www.ampltd.com

Technical support

Comprehensive technical information is available on our websites (see above).

If you can't find the information or solution you require, AMP has a team of technical support engineers / embedded video experts available to provide a quick *and free* response to your technical queries.

Please submit your technical support query to the appropriate email address:

Technical support US

E-mail: support@amp-usa.com

Technical support UK

E-mail: support@ampltd.com